



- Latest variant of the 07 preamplifier, featuring substantial active and passive component
- Balanced and unbalanced inputs and outputs
- Extremely low-noise circuitry with no overall feedback
- May be operated with included Coda universal remote control
- System logic remembers the most recent volume and balance settings for each input
- Wide bandwidth regulated supply with AC EMI and RFI line filter
- Double-sided gold plated circuit
- All anodized
- 10 year warranty / 5 year transferrable
- Designed, manufactured and assembled in the USA

Frequency Response: -3dB @ 5Hz to 200kHz

Distortion: <.005% from 10Hz to 40kHz @ 5V peak into 600Ω or higher shunted by 1000pF

Gain: Unbalanced Output: 12dB @ 1kHz
Balanced Output: 46db @ 1kHz

Maximum Output: 10V peak

Noise: <110dB referenced to 1V output

Input Impedance: 20kΩ

Output Impedance: 50Ω non-reactive unbalanced
100Ω non-reactive balanced

Crosstalk: 90dB @ 20kHz

Dimension: 18" W x 9.75" D x 2.5" H