



- 400 Watts per channel into 8 Ohms
- 800 Watts per channel into 4 Ohms
- Precision Bias Class A operation to 10 Watts, sliding to Class AB at higher output level
- True state-of-the-art high-performance, high-current amplifier in an affordable, hand crafted chassis
- Fully discrete FET differential input stage DC coupled to an ultra wideband bipolar output stage
- Very high linear damping with minimal feedback
- AC-coupled unbalanced input and true DC coupled balanced input
- 3.0kVA toroidal power transformer
- Low-impedance power supply filter capacitor array
- Power supply status indicators
- 10 year warranty / 5 year transferable
- Designed, manufactured and assembled in the USA

Rated Power:	V3:	400W/ch Class AB into 8Ω 800W/ch Class AB into 4Ω Class A ~8W
	V2:	250W/ch Class AB into 8Ω 500W/ch Class AB into 4Ω Class A ~12W
	V1:	150W/ch Class AB into 8Ω 300W/ch Class AB into 4Ω Class A ~18W
Bandwidth:		DC to 100kHz @ -3dB
Distortion:		<.03% from 10Hz to 20kHz @ 350 Watts
Gain:		26dB
Current Capability:		150 Amperes peak per channel
Noise:		-110dB
Input Impedance:		50kΩ balanced 1kΩ balanced
Output Impedance:		.04Ω from 20Hz to 20kHz
Power Supply:		3kVA toroidal power transformer. Dual independent rectification and 80,000uF of power supply filter capacitance
Dimension:		17" W x 14" D x 5.5" H
Weight :		62 lbs.